

Instruction for 1 channel RF control

Annex Depot Inc.
www.lightobject.com



Specification

Frequency: 433MHZ

Distance: 300ft

Power: 12V

Channel: 1

Output: Relay On/Off (NO COM NC)

Mode: Momentary, Toggle, Latched

Modes

J1, J2, J3 Open: Momentary

J1, J2 cap: Toggle

J2, J3 cap: Self latched (release when 2nd button is press or recycled power)

To erase all memory code, press and hold the Program Button for 10s (note: some model takes 25s to react).

Program receiver procedure

Hit the program button for 1s, the LED 1 will blink 1 time. Then press a button on the target remote and LED2 will blink. A 'click' sound from the relay and the process is completed.

